
SSI 9001 and SSI 9002

Instruction set of serial interface

Description



ERMA
Electronic GmbH

Warranty

For delivered products our "Allgemeine Lieferungs- und Zahlungsbedingungen" are effective. In no event ERMA-Electronic or its suppliers shall be liable for any other damages whatsoever (including, without limitation, damages for loss of business profits, business interruption or other pecuniary loss) arising out of or inability to use this product.

All products from ERMA-Electronic are warranted against defective material and workmanship for a period of two (2) years from date of delivery. If it is necessary to return the product to ERMA, the sender is responsible for shipping charges, freight, insurance and proper packaging to prevent breakage in transit. ERMA's warranty does not apply to defects resulting from action of the buyer, such mishandling, improper interfacing, operation outside of design limits, improper repair or unauthorized modification.

Trademarks

All trademarks they are named or portrayed in the text are registered trademarks of its owner. The trademarks are recognized by ERMA-Electronic.

CONTENTS

1. General	5
2. Communications protocol	5
3. General commands	7
3.1. Read the ENCODER-, MIN- and MAX-Value	7
3.2. Main reset	7
3.3. Type designation	7
3.4. Software version	8
3.5. Number of production	8
3.6. Date of production	8
4. Commands of configuration level (P-00)	9
4.1. Resolution (bits) of the encoder	9
4.2. Output code of the encoder	9
4.3. Master/Slave Mode	10
4.4. Clock for Master-Mode	10
4.5. Zero defination	11
4.6. Rotation direction	11
4.7. Scaling factor	12
4.8. Offset value	12
4.9. Decimal points	13
4.10. Data source of the display	13
4.11. Reset time of the MIN/MAX-memory	14
4.12. Function of digital user input 1	14
4.13. Function of digital user input 2	15
4.14. Function of push button '*'	15
4.15. Function of push button '-'	16
4.16. Function of push button '+'	16
4.17. Access-code	17
5. Commands of alarm output level (P-02)	18
5.1. Commands of alarm output 1	18
5.1.1. Data source for alarm output 1	18

5.1.2.	Switching logic of alarm output 1	18
5.1.3.	Alarm point of alarm output 1	19
5.1.4.	Hysteresis of alram output 1	19
5.1.5.	Release delay time of alarm output 1	20
5.1.6.	Operate delay time of alarm output 1	20
5.2.	Commands of alarm output 2	21
5.2.1.	Data source for alarm output 2	21
5.2.2.	Switching logic of alarm output 2	21
5.2.3.	Alarm point of alarm output 2	22
5.2.4.	Hysteresis of alarm output 2	22
5.2.5.	Release delay time of alarm output 2	23
5.2.6.	Operate delay time of alarm output 2	23
5.3.	Commands of alarm output 3 (Only SSI 9002)	24
5.3.1.	Data source for alarm output 3 (Only SSI 9002)	24
5.3.2.	Switching logic of alarm output 3 (Only SSI 9002)	24
5.3.3.	Alarm point of alarm output 3 (Only SSI 9002)	25
5.3.4.	Hysteresis of alarm output 3 (Only SSI 9002)	25
5.3.5.	Release delay time of alarm output 3 (SSI 9002)	26
5.3.6.	Operate delay time of alarm output 3 (SSI 9002)	26
5.4.	Commands of alarm output 4 (Only SSI 9002)	27
5.4.1.	Data source for alarm output 4 (Only SSI 9002)	27
5.4.2.	Switching logic of alarm output 4 (Only SSI 9002)	27
5.4.3.	Alarm point of alarm output 4 (Only SSI 9002)	28
5.4.4.	Hysteresis of alarm output 4 (Only SSI 9002)	28
5.4.5.	Release delay time of alarm output 4 (SSI 9002)	29
5.4.6.	Operate delay time of alarm output 4 (SSI 9002)	29
6.	Commands of analog output level (P-03) (Only SSI 9001)	30
6.1.	Data source for analog output (Only SSI 9001)	30
6.2.	Configuration of analog output (Only SSI 9001)	30
6.3.	Display value for min. analog output signal (SSI 9001)	31
6.4.	Display value for max. analog output signal (SSI9001)	31
7.	Commands of interface level (P-04)	32
7.1.	Interface address	32

7.2.	Interface baud rate	32
7.3.	Transmission-Mode of serial interface	33
7.4.	Timer of timer controlled Terminal-Mode	33
7.5.	Data source for serial interface	34
8.	Error message NAK	35
8.1.	Error word register	35
9.	Command overview	36

Stand : 04.04.2002
SI900XSA.PUB
Technical subjects to change

1. General

The digital instrument SSI 9001/2 can be equipped with a bidirectional RS 485 interface. The connection of the interfaces is specified in the manual of the instrument SSI 9001/2.

2. Communications protocol

The organization of the communications protocol is conformed to DIN ISO 1745. The information message consist of the transmission control character, the command and the optional data. The instrument SSI 9001/2 gives an answer to each command. A host waits for the answer and evaluates them.

Transmission parameters

baud rate : 300, 1200, 2400, 4800, 9600, 19200
parity : no
data bits : 8
stop bits : 1

Transmission format:

SOH	D	D	STX	C	C	C	X..X	ETX	BCC
-----	---	---	-----	---	---	---	------	-----	-----

Significance of the signs:

SOH (ASCII 01) : start of heading
D : address (decimal) of the instrument
STX (ASCII 02) : start of text
C : command signal sequence
ETX (ASCII 03) : optional data
BCC : end of text
BCC : control byte

ACK (ASCII 06) : positive acknowledge from the receiver
NAK (ASCII 21) : negative acknowledge from the receiver

Generation of the control byte:

Carry out an exclusive-OR operation (XOR) for all bytes between STX (exclusive) and ETX (inclusive). The byte can be used directly as the control byte, if the value is lower than 32. If the value of the control byte is higher than 32, it must be added 32 to them.

2. Communications protocol

Possible message formats

Return of datas:

STX	X..X	ETX	BCC
-----	------	-----	-----

Positive acknowledge:

ACK

Negative acknowledge (Errors):

NAK

Reasons of a negative acknowledge (Errors):

- command is unknown
- datas are wrong (to short or to long)
- datas contains wrong signs
- datas lies out of the value range
- wrong control byte

3. General commands

3.1. Read the ENCODER-, MIN- and MAX-Value

Read the ENCODER-Value

SOH	D	D	STX	M	S	W	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Read the MIN-Value

SOH	D	D	STX	M	I	N	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Read the MAX-Value

SOH	D	D	STX	M	A	X	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2 to the commands

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
 negative: ‘-’ (ASCII 2Dh)
 X ENCODER-, MIN- or MAX-Value
 valid values -99999 to 999999

3.2. Main reset

Carry out the main reset

SOH	D	D	STX	G	R	S	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

ACK

3.3. Type designation

Read the type designation

SOH	D	D	STX	G	E	R	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	S	S	I	9	0	0	1	X	ETX	BCC
-----	---	---	---	---	---	---	---	---	-----	-----

SSI 9001/2 type designation
 X X = 0 => no option analog output
 X = 1 => with option analog output

3.4. Software version

Read the software version

SOH	D	D	STX	V	E	R	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

X 000 to 099 => software version of the instrument

3.5. Number of production

Read the number of production

SOH	D	D	STX	S	R	N	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

X setting number of production

3.6. Date of production

Read the date of production

SOH	D	D	STX	D	A	T	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	0	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

X setting date of production

4. Commands of configuration level (P-00)

4.1. Resolution (bits) of the encoder

Read the setting of resolution (bits)

SOH	D	D	STX	B	I	T	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the resolution of the connected encoder

SOH	D	D	STX	B	I	T	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting the resolution of the connected encoder
valid values 010 to 025

Answer of SSI 9001/2

ACK

Example: Encoder with a resolution of 13 Bit

SOH	D	D	STX	B	I	T	0	1	3	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.2. Output code of the encoder

Read the setting code of the connected encoder

SOH	D	D	STX	G	B	C	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the code of the connected encoder

SOH	D	D	STX	G	B	C	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting code of the connected encoder
valid values 000 or 001

Answer of SSI 9001/2

ACK

Example: Output code Gray

SOH	D	D	STX	G	B	C	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.3. Master/Slave Mode

Read the setting mode of the SSI 9001/2

SOH	D	D	STX	M	S	B	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the mode

SOH	D	D	STX	M	S	B	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting mode of the SSI 9001/2
valid values 000 or 001

Answer of SSI 9001/2

ACK

Example: Slave-Mode

SOH	D	D	STX	M	S	B	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.4. Clock for Master-Mode

Read the setting clock of SSI 9001/2

SOH	D	D	STX	C	L	K	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the clock

SOH	D	D	STX	C	L	K	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting clock of SSI 9001/2
valid values 000 or 001

Answer of SSI 9001/2

ACK

Example: Clock = 200 kHz

SOH	D	D	STX	C	L	K	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.5. Zero defination

Read the setting number of zero defination

SOH	D	D	STX	N	U	L	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the zero defination of SSI 9001/2

SOH	D	D	STX	N	U	L	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of zero defination
valid values 000 or 001

Answer of SSI 9001/2

ACK

Example: Zero defination with ± display

SOH	D	D	STX	N	U	L	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.6. Rotation direction

Read the setting number of rotation direction

SOH	D	D	STX	D	I	R	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the rotation direction

SOH	D	D	STX	D	I	R	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of rotation direction
valid values 000 or 001

Answer of SSI 9001/2

ACK

Example: Rotation direction clockwise

SOH	D	D	STX	D	I	R	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.7. Scaling factor

Read the setting of the scaling factor

SOH	D	D	STX	S	C	A	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Set the scaling factor

SOH	D	D	STX	S	C	A	X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

X setting scaling factor
valid values 000001 to 999999

Answer of SSI 9001/2

ACK

Example: Scaling factor 1.56748

SOH	D	D	STX	S	C	A	1	5	6	7	4	8	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

Remark: Do not transfer the decimal point !

4.8. Offset value

Read the setting of offset value

SOH	D	D	STX	O	F	F	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the offset value

SOH	D	D	STX	O	F	F	V or X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)
X offset value
valid values -99999 to 999999

Answer of SSI 9001/2

ACK

Example: Offset value = 2.00000

SOH	D	D	STX	O	F	F	2	0	0	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

Remark: Do not transfer the decimal point !

4.9. Decimal points

Read the setting of decimal point

SOH	D	D	STX	A	N	K	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the decimal point of SSI 9001/2

SOH	D	D	STX	A	N	K	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of decimal point
valid values 000 to 005

Answer of SSI 9001/2

ACK

Example: Number of decimal point = 2

SOH	D	D	STX	A	N	K	0	0	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.10. Data source of the display

Read the setting of data source for the display

SOH	D	D	STX	A	N	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the data source for the display

SOH	D	D	STX	A	N	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of data source for the display
valid values 000 to 003

Answer of SSI 9001/2

ACK

Example: Data source for the display = 0 (Encoder value)

SOH	D	D	STX	A	N	D	0	0		ETX	BCC
-----	---	---	-----	---	---	---	---	---	--	-----	-----

4.11. Reset time of the MIN/MAX-memory

Read the setting of reset time for MIN/MAX-memory

SOH	D	D	STX	R	S	Z	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the reset time of MIN/MAX-memory

SOH	D	D	STX	R	S	Z	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting reset time in seconds
valid values 000 to 100

Answer of SSI 9001/2

ACK

Example: Reset time of MIN/MAX-memory = 10 (10 seconds)

SOH	D	D	STX	R	S	Z	0	1	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.12. Function of digital user input 1

Read the setting for the digital user input 1

SOH	D	D	STX	F	D	1	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the function for the digital user input 1

SOH	D	D	STX	F	D	1	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of the function for the digital user input 1
valid values 000 to 010

Answer of SSI 9001/2

ACK

Example: Function of the digital user input 1 = 7 (display test)

SOH	D	D	STX	F	D	1	0	0	7	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.13. Function of digital user input 2

Read the setting for the digital user input 2

SOH	D	D	STX	F	D	2	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the function for the digital user input 2

SOH	D	D	STX	F	D	2	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of the function for the digital user input 2
valid values 000 to 010

Answer of SSI 9001/2

ACK

Example: Function of digital user input 2 = 2 (Taring of encoder)

SOH	D	D	STX	F	D	2	0	0	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.14. Function of push button **

Read the setting of function for the push button *

SOH	D	D	STX	F	T	*	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the function of the push button *

SOH	D	D	STX	F	T	*	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of function for push button *
valid values 000 to 005

Answer of SSI 9001/2

ACK

Example: Function of push button * = 1 (Reset the MIN/MAX-memory)

SOH	D	D	STX	F	T	*	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.15. Function of push button '-'

Read the setting of function for the push button 

SOH	D	D	STX	F	T	-	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the function of push button 

SOH	D	D	STX	F	T	-	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of function for push button 
valid values 000 to 006

Answer of SSI 9001/2

ACK

Example: Function of push button  = 3 (display the MIN value)

SOH	D	D	STX	F	T	-	0	0	3	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.16. Function of push button '+'

Read the setting of push button 

SOH	D	D	STX	F	T	+	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the function of push button 

SOH	D	D	STX	F	T	+	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of function for push button 
valid values 000 to 006

Answer of SSI 9001/2

ACK

Example: Function of push button  = 2 (display the MAX value)

SOH	D	D	STX	F	T	+	0	0	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

4.17. Access-code

Read the setting of access-code

SOH	D	D	STX	C	O	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	V	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Setting the access-code

SOH	D	D	STX	C	O	D	V	0	0	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
X access-code
valid values 00000 to 00999

Answer of SSI 9001/2

ACK

Example: Access-code = 123

SOH	D	D	STX	C	O	D		0	0	1	2	3	ETX	BCC
-----	---	---	-----	---	---	---	--	---	---	---	---	---	-----	-----

5. Commands of alarm output level (P-02)

5.1. Commands of alarm output 1

5.1.1. Data source for alarm output 1

Read the setting of data source for the alarm output 1

SOH	D	D	STX	G	1	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the data source for the alarm output 1

SOH	D	D	STX	G	1	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of data source for the alarm output 1
valid values 000 to 004

Answer of SSI 9001/2

ACK

Example: Data source for alarm output 1 = 1 (Encoder value)

SOH	D	D	STX	G	1	D	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.1.2. Switching logic of alarm output 1

Read the setting of switching logic for the alarm output 1

SOH	D	D	STX	G	1	C	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the switching logic of alarm output 1

SOH	D	D	STX	G	1	C	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of switching logic for the alarm output 1
valid values 000 to 003

Answer of SSI 9001/2

ACK

Example: Switching logic of alarm output 1 = 1 (contact closed at high limit)

SOH	D	D	STX	G	1	C	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.1.3. Alarm point of alarm output 1

Read the setting of alarm point for alarm output 1

SOH	D	D	STX	G	1	W	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the alarm point of alarm output 1

SOH	D	D	STX	G	1	W	V or X	X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	---	-----	-----

V sign
positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)

X alarm point
valid values -99999 to 999999

Answer of SSI 9001/2

ACK

Example: Alarm point of alarm output 1 = 2500

SOH	D	D	STX	G	1	W		0	0	2	5	0	0	ETX	BCC
-----	---	---	-----	---	---	---	--	---	---	---	---	---	---	-----	-----

5.1.4. Hysteresis of alram output 1

Read the setting of hysteresis for the alarm output 1

SOH	D	D	STX	G	1	H	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Set the hysteresis of alarm output 1

SOH	D	D	STX	G	1	H	0	0	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

X hysteresis
valid values 000001 to 001000

Answer of SSI 9001/2

ACK

Example: Hysteresis of alarm output 1 = 100

SOH	D	D	STX	G	1	H	0	0	0	1	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

5.1.5. Release delay time of alarm output 1

Read the setting of release delay time for the alarm output 1

SOH	D	D	STX	G	1	F	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the release delay time of alarm output 1

SOH	D	D	STX	G	1	F	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X release delay time in seconds
valid values 000 to 060

Answer of SSI 9001/2

ACK

Example: Release delay time of alarm output 1 = 0 (no release delay time)

SOH	D	D	STX	G	1	F	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.1.6. Operate delay time of alarm output 1

Read the setting of operate delay time for alarm output 1

SOH	D	D	STX	G	1	S	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the operate delay time of alarm output 1

SOH	D	D	STX	G	1	S	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X operate delay time in seconds
valid values 000 to 0 60

Answer of SSI 9001/2

ACK

Example: Operate delay time of alarm output 1 = 12 (12 seconds)

SOH	D	D	STX	G	1	S	0	1	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.2. Commands of alarm output 2

5.2.1. Data source for alarm output 2

Read the setting of data source for the alarm output 2

SOH	D	D	STX	G	2	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the data source for the alarm output 2

SOH	D	D	STX	G	2	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of data source for the alarm output 2
valid values 000 to 004

Answer of SSI 9001/2

ACK

Example: Data source for alarm output 2 = 1 (Encoder value)

SOH	D	D	STX	G	2	D	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.2.2. Switching logic of alarm output 2

Read the setting of switching logic for the alarm output 2

SOH	D	D	STX	G	2	C	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the switching logic of alarm output 2

SOH	D	D	STX	G	2	C	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of switching logic for the alarm output 1
valid values 000 to 003

Answer of SSI 9001/2

ACK

Example: Switching logic of alarm output 2 = 1 (contact closed at high limit)

SOH	D	D	STX	G	2	C	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.2.3. Alarm point of alarm output 2

Read the setting of alarm point for alarm output 2

SOH	D	D	STX	G	2	W	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the alarm point of alarm output 2

SOH	D	D	STX	G	2	W	V or X	X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)

X alarm point valid values -99999 to 999999

Answer of SSI 9001/2

ACK

Example: Alarm point of alarm output 2 = - 5000

SOH	D	D	STX	G	2	W	-	0	5	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

5.2.4. Hysteresis of alarm output 2

Read the setting of hysteresis for alarm output 2

SOH	D	D	STX	G	2	H	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Set the hysteresis of alarm output 2

SOH	D	D	STX	G	2	H	0	0	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

X hysteresis valid valuese 000001 to 001000

Answer of SSI 9001/2

ACK

Example: Hysteresis of alarm output 2 = 125

SOH	D	D	STX	G	2	H	0	0	1	2	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	-----	-----

5.2.5. Release delay time of alarm output 2

Read the setting of release delay time for alarm output 2

SOH	D	D	STX	G	2	F	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the release delay time of alarm output 2

SOH	D	D	STX	G	2	F	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X release delay time in seconds
valid values 000 to 060

Answer of SSI 9001/2

ACK

Example: Release delay time of alarm output 2 = 5 (5 seconds)

SOH	D	D	STX	G	2	F	0	0	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.2.6. Operate delay time of alarm output 2

Read the setting of operate delay time for alarm output 2

SOH	D	D	STX	G	2	S	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the operate delay time of alarm output 2

SOH	D	D	STX	G	2	S	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X operate delay time in seconds
valid values 000 to 060

Answer of SSI 9001/2

ACK

Example: Operate delay time of alarm output 2 = 22 (22 seconds)

SOH	D	D	STX	G	2	S	0	2	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.3. Commands of alarm output 3 (Only SSI 9002)

5.3.1. Data source for alarm output 3 (Only SSI 9002)

Read the setting of data source for the alarm output 3

SOH	D	D	STX	G	3	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the data source for the alarm output 3

SOH	D	D	STX	G	3	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of data source for the alarm output 2
valid values 000 to 004

Answer of SSI 9002

ACK

Example: Data source for alarm output 3 = 1 (Encoder value)

SOH	D	D	STX	G	3	D	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.3.2. Switching logic of alarm output 3 (Only SSI 9002)

Read the setting of switching logic for the alarm output 3

SOH	D	D	STX	G	3	C	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the switching logic of alarm output 3

SOH	D	D	STX	G	3	C	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of switching logic for the alarm output 1
valid values 000 to 003

Answer of SSI 9002

ACK

Example: Switching logic of alarm output 3 = 1 (contact closed at high limit)

SOH	D	D	STX	G	3	C	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.3.3. Alarm point of alarm output 3 (Only SSI 9002)

Read the setting of alarm point for alarm output 3

SOH	D	D	STX	G	3	W	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the alarm point of alarm output 3

SOH	D	D	STX	G	3	W	V or X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)

X alarm point valid values -99999 to 999999

Answer of SSI 9002

ACK

Example: Alarm point of alarm output 3 = - 5000

SOH	D	D	STX	G	3	W	-	0	5	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

5.3.4. Hysteresis of alarm output 3 (Only SSI 9002)

Read the setting of hysteresis for alarm output 3

SOH	D	D	STX	G	3	H	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Set the hysteresis of alarm output 3

SOH	D	D	STX	G	3	H	0	0	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

X hysteresis valid valuese 000001 to 001000

Answer of SSI 9002

ACK

Example: Hysteresis of alarm output 3 = 125

SOH	D	D	STX	G	3	H	0	0	1	2	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	-----	-----

5.3.5. Release delay time of alarm output 3 (Only SSI 9002)

Read the setting of release delay time for alarm output 3

SOH	D	D	STX	G	3	F	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the release delay time of alarm output 3

SOH	D	D	STX	G	3	F	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X release delay time in seconds
valid values 000 to 060

Answer of SSI 9002

ACK

Example: Release delay time of alarm output 3 = 5 (5 seconds)

SOH	D	D	STX	G	3	F	0	0	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.3.6. Operate delay time of alarm output 3 (Only SSI 9002)

Read the setting of operate delay time for alarm output 3

SOH	D	D	STX	G	3	S	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the operate delay time of alarm output 3

SOH	D	D	STX	G	3	S	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X operate delay time in seconds
valid values 000 to 060

Answer of SSI 9002

ACK

Example: Operate delay time of alarm output 3 = 22 (22 seconds)

SOH	D	D	STX	G	3	S	0	2	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.4. Commands of alarm output 4 (Only SSI 9002)

5.4.1. Data source for alarm output 4 (Only SSI 9002)

Read the setting of data source for the alarm output 4

SOH	D	D	STX	G	4	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the data source for the alarm output 4

SOH	D	D	STX	G	4	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of data source for the alarm output 2
valid values 000 to 004

Answer of SSI 9002

ACK

Example: Data source for alarm output 4 = 1 (Encoder value)

SOH	D	D	STX	G	4	D	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.4.2. Switching logic of alarm output 4 (Only SSI 9002)

Read the setting of switching logic for the alarm output 4

SOH	D	D	STX	G	4	C	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the switching logic of alarm output 4

SOH	D	D	STX	G	4	C	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of switching logic for the alarm output 1
valid values 000 to 003

Answer of SSI 9002

ACK

Example: Switching logic of alarm output 4 = 1 (contact closed at high limit)

SOH	D	D	STX	G	4	C	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.4.3. Alarm point of alarm output 4 (Only SSI 9002)

Read the setting of alarm point for alarm output 4

SOH	D	D	STX	G	4	W	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the alarm point of alarm output 4

SOH	D	D	STX	G	4	W	V or X	X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)

X alarm point valid values -99999 to 999999

Answer of SSI 9002

ACK

Example: Alarm point of alarm output 4 = - 5000

SOH	D	D	STX	G	4	W	-	0	5	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

5.4.4. Hysteresis of alarm output 4 (Only SSI 9002)

Read the setting of hysteresis for alarm output 4

SOH	D	D	STX	G	4	H	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Set the hysteresis of alarm output 4

SOH	D	D	STX	G	4	H	0	0	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

X hysteresis valid valuese 000001 to 001000

Answer of SSI 9002

ACK

Example: Hysteresis of alarm output 4 = 125

SOH	D	D	STX	G	4	H	0	0	1	2	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	-----	-----

5.4.5. Release delay time of alarm output 4 (Only SSI 9002)

Read the setting of release delay time for alarm output 4

SOH	D	D	STX	G	4	F	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the release delay time of alarm output 4

SOH	D	D	STX	G	4	F	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X release delay time in seconds
valid values 000 to 060

Answer of SSI 9002

ACK

Example: Release delay time of alarm output 4 = 5 (5 seconds)

SOH	D	D	STX	G	4	F	0	0	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

5.4.6. Operate delay time of alarm output 4 (Only SSI 9002)

Read the setting of operate delay time for alarm output 4

SOH	D	D	STX	G	4	S	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9002

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the operate delay time of alarm output 4

SOH	D	D	STX	G	4	S	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X operate delay time in seconds
valid values 000 to 060

Answer of SSI 9002

ACK

Example: Operate delay time of alarm output 4 = 22 (22 seconds)

SOH	D	D	STX	G	4	S	0	2	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

6. **Commands of analog output level (P-03) (Only SSI 9001)**

6.1. **Data source for analog output (Only SSI 9001)**

Read the setting of data source for the analog output

SOH	D	D	STX	D	A	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the data source of analog output

SOH	D	D	STX	D	A	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of data source for the analog output
valid values 000 to 003

Answer of SSI 9001

ACK

Example: Data source for analog output = 1 (MAX value)

SOH	D	D	STX	D	A	D	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

6.2. **Configuration of analog output (Only SSI 9001)**

Read the setting of configuration for analog output

SOH	D	D	STX	D	A	C	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the configuration of analog output

SOH	D	D	STX	D	A	C	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of configuration for the analog output
valid values 000 to 003

Answer of SSI 9001

ACK

Example: Configuration of analog output = 2 (0 to 20 mA)

SOH	D	D	STX	D	A	C	0	0	2	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

6.3. Display value for min. analog output signal (Only SSI 9001)

Read the display value for minimal analog output signal

SOH	D	D	STX	D	A	A	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the display value for minimal analog output signal

SOH	D	D	STX	D	A	A	V or X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)

X display value
valid values -99999 to 999999

Answer of SSI 9001

ACK

Example: Display value for minimal analog output signal = -1000

SOH	D	D	STX	D	A	A	-	0	1	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

6.4. Display value for max. analog output signal (Only SSI9001)

Read the display value for the maximal analog output signal

SOH	D	D	STX	D	A	E	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001

STX	V or X	X	X	X	X	X	ETX	BCC
-----	--------	---	---	---	---	---	-----	-----

Set the display value for the maximal analog output signal

SOH	D	D	STX	D	A	E	V or X	X	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	--------	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)
negative: ‘-’ (ASCII 2Dh)

X display value
valid values -99999 to 999999

Answer of SSI 9001

ACK

Example: Display value for maximal analog output signale = 10000

SOH	D	D	STX	D	A	E	0	1	0	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

7. Commands of interface level (P-04)

7.1. Interface address

Read the address of the serial interface

SOH	D	D	STX	R	S	A	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the address of the serial interface

SOH	D	D	STX	R	S	A	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X address of the serial interface
valid values 0 to 31

Answer of SSI 9001/2

ACK

Example: interface address = 5

SOH	D	D	STX	R	S	A	0	0	5	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

7.2. Interface baud rate

Read the setting of baud rate for the serial interface

SOH	D	D	STX	R	S	B	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set the baud rate of the serial interface

SOH	D	D	STX	R	S	B	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X setting number of baud rate for the serial interface
valid values 0 to 6

Answer of SSI 9001/2

ACK

Example: number of baudrate = 6 (19200 baud)

SOH	D	D	STX	R	S	B	0	0	6	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

7.3. Transmission-Mode of serial interface

Read the transmission-mode of serial interface

SOH	D	D	STX	R	S	M	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set transmission-mode of serial interface

SOH	D	D	STX	R	S	M	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X number of transmission-mode
valid values 000 bis 002

Answer of SSI 9001/2

ACK

Example: Number of transmission-mode = 0 (PC-Mode)

SOH	D	D	STX	R	S	M	0	0	0	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

7.4. Timer of timer controlled Terminal-Mode

Read Timer

SOH	D	D	STX	R	T	T	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	V	0	X	X	X	X	ETX	BCC
-----	---	---	---	---	---	---	-----	-----

Set Timer

SOH	D	D	STX	R	T	T	V	0	X	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	---	---	---	-----	-----

V sign positive: ‘‘ (ASCII 20h)

X timer (Sendrate in sec.)
valid values 00000 bis 03600

Answer of SSI 9001/2

ACK

Example: Timer (Sendrate = 60 sec.)

SOH	D	D	STX	R	T	T		0	0	0	6	0	ETX	BCC
-----	---	---	-----	---	---	---	--	---	---	---	---	---	-----	-----

7.5. Data source for serial interface

Read data source of Terminal-Mode

SOH	D	D	STX	R	S	D	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Set data source of Terminal-Mode

SOH	D	D	STX	R	S	D	X	X	X	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

X data source of Terminal-Mode
valid values 000 bis 003

Answer of SSI 9001/2

ACK

Example: Data source of Terminal-Mode = 1 (Max-value)

SOH	D	D	STX	R	S	D	0	0	1	ETX	BCC
-----	---	---	-----	---	---	---	---	---	---	-----	-----

8. Error message NAK

Reasons for a error message

- command is unknown
- datas lies out of the valid value range
- datas are wrong (to short or to long)
- the instrument SSI 9001/2 is in the programming mode
(Each command is receipt with a *NAK*, when the instrument is in the programming mode)

8.1. Error word register

Read the error word register

SOH	D	D	STX	E	R	R	ETX	BCC
-----	---	---	-----	---	---	---	-----	-----

Answer of SSI 9001/2

STX	X	X	X	ETX	BCC
-----	---	---	---	-----	-----

Explanation of error word register

Error word register	Significance
0	no error
10	command unknown
11	datas are wrong (to shortz)
12	datas are wrong (to long)
13	datas contains wrong signs
14	datas lies out of the valid value range
15	wrong control byte

A error word be preserved as long as the error word register is read through. After the reading the error word register is cleared.

9. Command overview

AND	read or set the data source for the display
ANK	read or set the decimal points
BIT	read or set the resolution (bits) of the connected encoder
CLK	read or set the clock of the master-mode
COD	read or set the access-code for the programming
DAA	read/set the display value for the min. analog output signal (Only SSI9001)
DAC	read or set the configuration of the analog output (Only SSI9001)
DAD	read or set the data source for the analog output (Only SSI 9001)
DAE	read/set the display value for the max. analog output signal(Only SSI9001)
DAT	read the data of production
DIR	read or set rotation direction
ERR	read the error word register
FD1	read or set the function of the digital user input 1
FD2	read or set the function of the digital user input 2
FT*	read or set the function of push button “ * ”
FT-	read or set the function of push button “ - ”
FT+	read or set the function of push button “ + ”
GBR	read or set the output code of the connected encoder
GER	read the type designation
GRS	carried out the main reset
G1C	read or set the switching logic of alarm output 1
G1D	read or set the data source for alarm output 1
G1F	read or set the release delay time of alarm output 1
G1H	read or set the hysteresis of alarm output 1
G1S	read or set the operate delay time of alarm output 1
G1W	read or set the alarm point of alarm output 1
G2C	read or set the switching logic of alarm output 2

9. Command overview

G2D	read or set the data source for alarm output 2
G2F	read or set the release delay time of alarm output 2
G2H	read or set the hysteresis of alarm output 2
G2S	read or set the operate delay time of alarm output 2
G2W	read or set the alarm point of alarm output 2
G3C	read or set the switching logic of alarm output 3 (Only SSI 9002)
G3D	read or set the data source for alarm output 3 (Only SSI 9002)
G3F	read or set the release delay time of alarm output 3(Only SSI 9002)
G3H	read or set the hysteresis of alarm output 3 (Only SSI 9002)
G3S	read or set the operate delay time of alarm output 3(Only SSI9002)
G3W	read or set the alarm point of alarm output 3 (Only SSI 9002)
G4C	read or set the switching logic of alarm output 4 (Only SSI 9002)
G4D	read or set the data source for alarm output 4 (Only SSI9002)
G4F	read or set the release delay time of alarm output 4 (Only SSI9002)
G4H	read or set the hysteresis of alarm output 4 (Only SSI 9002)
G4S	read or set the operate delay time of alarm output 4(Only SSI9002)
G4W	read or set the alarm point of alarm output 4 (Only SSI 9002)
MAX	read the MAX value
MIN	read the MIN value
MSB	read or set the mode master or the mode slave
MSW	read the MEASURED value
NUL	read or set the zero defination
OFF	read or set the offset value
RSA	read or set the interface address
RSB	read or set the baud rate of the interface
RSZ	read or set the reset time of MIN/MAX-memory
SCA	read or set the scaling factor
SRN	read or set the number of production
VER	read the software version

ERMA - Electronic GmbH
Max-Eyth-Straße 8
D-78194 Immendingen

Telefon (+49 7462) 7381
Fax (+49 7462) 7554
email erma-electronic@t-online.de

